

Low Addr	D31	D30	D29	D28	High Addr	D31	D30	D29	D28		comment
00	1	0	0	0	100	0	0	1	1	er_Type	Z3+256K+norom
04	0	0	0	0	104	0	0	1	0	er_Product	#2
08	0	1	0	1	108	0	0	0	0	er_Flags	I/O dev, unext.
0C	0	0	0	0	10C	0	0	0	0	er_Reserved03	
10	0	0	0	0	110	0	1	1	1	er_Manufacturer	Hacker
14	1	1	0	1	114	1	0	1	1	er_Manufacturer	2011 = \$7DB
18	0	0	0	0	118	0	0	0	0	er_SerialNumber	S/N: 0001
1C	0	0	0	0	11C	0	0	0	0	er_SerialNumber	
20	0	0	0	0	120	0	0	0	0	er_SerialNumber	
24	0	0	0	0	124	0	0	0	1	er_SerialNumber	
28	0	0	0	0	128	0	0	0	0	er_InitDiagVec	No Boot Rom
2C	0	0	0	0	12C	0	0	0	0	er_InitDiagVec	
30	0	0	0	0	130	0	0	0	0	er_Reserved0c	
34	0	0	0	0	134	0	0	0	0	er_Reserved0d	
38	0	0	0	0	138	0	0	0	0	er_Reserved0e	
3C	0	0	0	0	13C	0	0	0	0	er_Reserved0f	
40	0	0	0	0	140	0	0	0	0	er_Interrupt	
44	X	X	X	X	144	X	X	X	X	ec_Z3_HighByte	PIC Address
48	X	X	X	X	148	X	X	X	X	ec_BaseAddress	16-bit
4C	X	X	X	X	14C	X	X	X	X	er_Shutup	Shutup reg
50	0	0	0	0	150	0	0	0	0	Reserved	mut be 0
...	0	0	0	0	0	0	0	0	...	mut be 0
7C	0	0	0	0	17C	0	0	0	0	Reserved	mut be 0

Zorro III AutoConfig ROM Table V0.98

All Registers Except 00/100 must be inverted